SOUND POWERED TELEPHONE SYSTEM

Direct-Way Waterproof Type Marine Batteryless Sound Powered Telephone

ISO9001 Supplier

Class Certificate

Export Supply

Specification: It is used as sound powered and common battery telephones for communication on vessels. Loud Clear HSC Sound powered telephone Telephone System The series of HSC sound powered telep...



Key Highlights

Category	Sound Powered Telephone System
Standard	DIN
Certificate	ABS, LR, BV, DNVGL, NK, KR, IRS, RMRS, CCS

We can supply according to your requirement, drawings, class certificate needs, and delivery schedule.

Technical Specifications

Category	Sound Powered Telephone System	**Model / SKU**	Direct-Way-Waterproof-Type-Marine-Batteryless-Sound-Powered-Telephone
Standard	DIN	**Certificate**	ABS, LR, BV, DNVGL, NK, KR, IRS, RMRS, CCS
Warranty	12 Months unless specified otherwise	**Origin**	China

CONTENTS

- Specification:
- System configuration can be classfied into three types.
- FEATURES

Specification:

It is used as sound powered and common battery telephones for communication on vessels.

Loud
Clear

HSC Sound powered telephone Telephone System

The series of HSC sound powered telephone telephones are designed according to the CCS rules and regulations.They are used as sound powered and common battery telephones for communication on vessels. Its features are loud and clear with or without external power, and convenient for use.

FEATURES

Enhance voice for communicate

The user can use the sound powered telephone telephone with 24VDC power to communicate. The telephone call will change to sound powered call automatically when power down.

Press key to call

One call key on the panel of the HSC telephone. When the 24VDC power is on, press this key to call the other telephone without rotating the generator. When the power supply is between 15V and 35V, the telephone can be used normally. Rotate the generator to communicate when power down.

Noise-proof feature

The noise-proof sound powered telephone telephone with noise-proof headset. It can be used under the 110dB noise enviornement.

Flashing light signalling unit

It is used in the engine room and other noise area. The sound powered telephone telephones all with terminals to connect it. When the telephone call signal should be send to the E/R alarm indicator column, FR-100 relay box should be connected.

System configuration can be classfied into three types.

1. Single-way sound powered telephone telephone

Two single-way sound powered telephone telephones can be connected for communication. When the cable of HSC-1Q connect through wheelhouse console, the connection cable should be separated screen and grounded well.

2. Selective sound powered telephone telephone

The selective call telephone system is consisted of several multi-way type telephones. Any telephone can call each

other. Several pairs of telephones can communicate at the same time. The capability is 4~12 lines.

3. Command sound powered telephone telephone

The command sound powered telephone telehone system is consisted of one command telephone and several multi-way type telephones. The command telephone can communicate with multi-way type telephones. The multi-way telephone can not call each other. Other telephones can override when the command telephone communicate with the others.