ELECTRIC HEATER

ZJ20K Gear Fast Heater

ZJ20K Gear Fast Heater   ZJ20K gear quick heater is used for heating gears, couplings, motor shells, bearing caps and other parts of power, transmission machinery, gearboxes and other transmission parts to...

ISO9001 Supplier

Class Certificate

Export Supply



Key Highlights

Category	Electric Heater
Standard	EN
Weight / Size	Model ZJ20K--I --II --III --IV --V --VI --VII --IIX Rated powe...
Certificate	ABS, LR, BV, DNVGL, NK, KR, IRS, RMRS, CCS

We can supply according to your requirement, drawings, class certificate needs, and delivery schedule.

Technical Specifications

Category	Electric Heater	**Model / SKU**	ZJ20K-Gear-Fast-Heater
Standard	EN	**Weight / Size**	Model ZJ20K--I --II --III --IV --V --VI --VII --IIX Rated power (KVA) 3.8 5.5 9.5 11.5 22 34 41.5 60 Rated voltage (V) 380 380 380 380 380 380 380 380 Rated current (A) 10 15 25 30 60 90 110 160 Heating the workpiece Inner diameter (mm) 10-25 10-40 10-70 10-90 30-110 30-110 30-120 30-120 Maximum outer diameter(mm) 70 80 100 120 300 450 600 800 Width(mm) 30 35 35 50 50-150 70-170 80-180 90-200 Weight (Kg) 45 58 90 145 205 370 450 500
Certificate	ABS, LR, BV, DNVGL, NK, KR, IRS, RMRS, CCS	**Warranty**	12 Months unless specified otherwise
Origin	China		

China ZJ20K Gear Fast Heater:

ZJ20K Gear Fast Heater

ZJ20K gear quick heater is used for heating gears, couplings, motor shells, bearing caps and other parts of power, transmission machinery, gearboxes and other transmission parts to meet the needs of interference assembly.

Model		ZJ20K--I	--II	--III	--IV	--V	--VI	--VII	--IIX
Rated power (KVA)		3.8	5.5	9.5	11.5	22	34	41.5	60
Rated voltage (V)		380	380	380	380	380	380	380	380
Rated current (A)		10	15	25	30	60	90	110	160
Heating the workpiece	Inner diameter (mm)	10-25	10-40	10-70	10-90	30-110	30-110	30-120	30-120
	Maximum outer diameter(mm)	70	80	100	120	300	450	600	800
	Width(mm)	30	35	35	50	50-150	70-170	80-180	90-200
Weight (Kg)		45	58	90	145	205	370	450	500