

MARINE TRANSFORMERS

JDZ-10 Voltage Transformer

JDZ-10 Voltage Transformer The product complies with standards GB1207 and IEC186 JDZ-10 Voltage Transformer Parameters Model Rated Voltage Ratio/V ...

ISO9001 Supplier

Class Certificate

Export Supply



Key Highlights

|             |                                            |
|-------------|--------------------------------------------|
| Category    | Marine Transformers                        |
| Standard    | GB                                         |
| Certificate | ABS, LR, BV, DNVGL, NK, KR, IRS, RMRS, CCS |

We can supply according to your requirement, drawings, class certificate needs, and delivery schedule.

Technical Specifications

|          |                                      |             |                                            |
|----------|--------------------------------------|-------------|--------------------------------------------|
| Category | Marine Transformers                  | Model / SKU | JDZ-10-Voltage-Transformer                 |
| Standard | GB                                   | Certificate | ABS, LR, BV, DNVGL, NK, KR, IRS, RMRS, CCS |
| Warranty | 12 Months unless specified otherwise | Origin      | China                                      |

CONTENTS

- JDZ-10 Voltage Transformer
- JDZ-10 Voltage Transformer Parameters
- JDZ-10 Voltage Transformer Drawing

JDZ-10 Voltage Transformer

The product complies with standards GB1207 and IEC186

JDZ-10 Voltage Transformer Parameters

|       |                       |                    |
|-------|-----------------------|--------------------|
| Model | Rated Voltage Ratio/V | Rated Frequency/Hz |
|-------|-----------------------|--------------------|

|         |                                              |       |
|---------|----------------------------------------------|-------|
| JDZ-3   | 1000/100<br>2000/100<br>3000/100             | 50,60 |
| JDZ-6   | 6000/100                                     |       |
| JDZ-10  | 10000/100<br>10000/100/100                   |       |
| JDZJ-3  | 2000/√3/100/√3/100/3<br>3000/√3/100/√3/100/3 |       |
| JDZJ-6  | 6000/√3/100/√3/100/3                         |       |
| JDZJ-10 | 10000/√3/100/√3/100/3                        |       |

| Model   | Rated Output/VA |           |         |         |          | Ultimate Output /VA |
|---------|-----------------|-----------|---------|---------|----------|---------------------|
|         | 0.2 grade       | 0.5 grade | 1 grade | 3 grade | 6P grade |                     |
| JDZ-3   | /               | 30        | 50      | 80      | /        | 200                 |
| JDZ-6   | /               | 50        | 80      | 200     | /        | 400                 |
| JDZ-10  | /               | 80        | 150     | 300     | /        | 500                 |
|         | 40              | /         | /       | /       | /        | 200                 |
|         | 25              | 50        | /       | /       | /        | 200                 |
| JDZJ-3  | /               | 30        | 50      | 80      | 50       | 200                 |
| JDZJ-6  | /               | 50        | 80      | 200     | 50       | 400                 |
| JDZJ-10 | /               | 50        | 80      | 200     | 50       | 400                 |
|         | 20              | /         | /       | /       | 50       | 200                 |

JDZ-10 Voltage Transformer Drawing

