

MARINE TRANSFORMERS

JDZX10-6B Voltage Transformer

JDZX10-6B Voltage Transformer 1. The product complies with standards GB1207 and IEC186 2. This series of products includes three voltage transformers: JDZ10-3B, 6B1, 10B1, JDZX10-3B1, 6B1, 10B1, JDZX10-3B, 6B, 10B...

ISO9001 Supplier

Class Certificate

Export Supply



Key Highlights

|             |                                            |
|-------------|--------------------------------------------|
| Category    | Marine Transformers                        |
| Standard    | GB                                         |
| Certificate | ABS, LR, BV, DNVGL, NK, KR, IRS, RMRS, CCS |

We can supply according to your requirement, drawings, class certificate needs, and delivery schedule.

Technical Specifications

|          |                                      |             |                                            |
|----------|--------------------------------------|-------------|--------------------------------------------|
| Category | Marine Transformers                  | Model / SKU | JDZX10-6B-Voltage-Transformer              |
| Standard | GB                                   | Certificate | ABS, LR, BV, DNVGL, NK, KR, IRS, RMRS, CCS |
| Warranty | 12 Months unless specified otherwise | Origin      | China                                      |

CONTENTS

- JDZX10-6B Voltage Transformer
- JDZX10-6B Voltage Transformer Parameters
- JDZX10-6B Voltage Transformer Drawing

JDZX10-6B Voltage Transformer

1. The product complies with standards GB1207 and IEC186
2. This series of products includes three voltage transformers: JDZ10-3B, 6B1, 10B1, JDZX10-3B1, 6B1, 10B1, JDZX10-3B, 6B, 10B

## JDZX10-6B Voltage Transformer Parameters

| Model       | Rated Voltage Ratio/V | Rated Frequency/Hz | Rated Output/VA |           |         |           | Rated Insulation Level/KV |
|-------------|-----------------------|--------------------|-----------------|-----------|---------|-----------|---------------------------|
|             |                       |                    | 0.2 grade       | 0.5 grade | 1 grade | 6P grade  |                           |
| JDZ10-3B1   | 3000/100              | 50.6               | 25              | 50        | 90      | 3.6/25/40 |                           |
| JDZ10-6B1   | 6000/100              |                    | 25              | 50        | 90      | 7.2/32/60 |                           |
| JDZ10-10B1  | 10000/100             |                    | 25              | 50        | 90      | 12/42/75  |                           |
| JDZX10-3B1  | 3000/√3/100/√3/100/3  |                    | /               | 50        | 90      | 50        | 3.6/25/40                 |
| JDZX10-6B1  | 6000/√3/100/√3/100/3  |                    | /               | 50        | 90      | 50        | 7.2/32/60                 |
| JDZX10-10B1 | 10000/√3/100/√3/100/3 |                    | /               | 50        | 90      | 50        | 12/42/75                  |
| JDZX10-3B   | 3000/√3/100/√3/100/3  |                    | 25              | 50        | 90      | 50        | 3.6/25/40                 |
| JDZX10-6B   | 6000/√3/100/√3/100/3  |                    | 25              | 50        | 90      | 50        | 7.2/32/60                 |
| JDZX10-10B  | 10000/√3/100/√3/100/3 |                    | 25              | 50        | 90      | 50        | 12/42/75                  |

## JDZX10-6B Voltage Transformer Drawing

